

BPC-RK3576-01

Box PC



BPC-RK3576-01 Box PC



Overview:

BPC-RK3576-01 is a fanless mini box PC utilizing DEBIX R3576-01 SBC for default, and it supports adding a PoE module for the DEBIX SBC inside. It's an easy to use computer with a pre-installed image on the eMMC. Connect the display, power it on and press the ON/OFF button, then you can see the startup screen.

Main Features:

- Compact size, durable aluminum alloy case
- Fanless design with increased surface area for enhanced heat dissipation
- Two gigabit network ports and three USB 3.0 ports to bring an efficient data transmission speed
- 1 x HDMI port, 1 x 3.5mm headphone and mic combo port
- Support Wi-Fi antenna by removing the plastic baffle at the right side

Specification:

System	
Motherboard	DEBIX R3576-01
Memory	2GB LPDDR4 (4GB/8GB optional)
Storage	1) Default: Onboard 32GB eMMC (8GB/16GB/64GB/128GB/256GB optional) 2) Micro SD card 8GB/16GB/32GB/64GB/128GB/256GB optional
OS	Android 14, Debian 12
Boot Mode	Boot from eMMC
I/O Interfaces	
Gigabit Network	2 x Gigabit Ethernet Interfaces: 1) 1 x RJ45 with PoE power supply (needs PoE power supply module) 2) 1 x RJ45
Wi-Fi & BT	2.4GHz & 5GHz Wi-Fi 6, BT 5.4, external Wi-Fi SMA antenna connector
HDMI	1 x HDMI output with Type-A HDMI female
Audio	1 x 3.5mm headphone and microphone combo port
DP	1 x DP display supports MST with Type-C
USB	2 x USB 3.0 Host with double layer Type-A 1 x USB 2.0 PWR with Type-C for DC 5V power input 1 x USB 3.0 OTG + DP DISPLAY supports MST with Type-C
Power Supply	
Power Input	Default DC 5V/3A power input with Type-C interface
Mechanical & Environmental	
Size (L x W)	93.0mm x 72.0mm x 30.0mm (±0.5mm)
Net Weight	197g (±0.5g)
Gross Weight	218g (±0.5g)
Enclosure Material	Aluminum alloy
Operating Temp.	0°C ~ 70°C

I/O Interfaces and Dimension:



Compatible with DEBIX's Accessories:

Product	Model
SBC POE Board	EMB-AS-06
DEBIX Display Screen	DEBIX TD050H DEBIX TD070H DEBIX TD101H

Safety Instruction:

To avoid malfunction or damage to this product please observe the following:

- Disconnect the device from the DC power supply before cleaning. Use a damp rag. Do not use liquid detergents or spray-on detergents.
- Keep the device away from moisture.
- During installation, put the device on a reliable table. It will be damaged if you drop it.
- Before connecting the power supply, ensure that the voltage is in the required range.
- Put the power cable in place to avoid stepping on it.
- If the device is not used for a long time, power it off to avoid damage caused by sudden overvoltage.
- For safety reasons, the device can only be disassembled by professional personnel.
- Do not place the device in a place where the ambient temperature is below 0 °C or above 70 °C. This will damage the machine. It needs to be kept in an environment at controlled temperature.

Contact Us:

Headquarters: DEBIX Technology Inc., 8345 Gold River Ct., Las Vegas, NV 89113, USA

Factory: 5-6/F., East Zone, Shunheda A2 Building, Liuxiandong Industrial Park, Xili, Nanshan Dist., Shenzhen, China

Email: info@debix.io

Website: www.debix.io

Community: <https://discord.com/invite/adaHHaDkH2>

